



**Arab Academy for Science & Technology
and Maritime Transport – Cairo Branch
College of Engineering & technology
Electronics & Communication Engineering Department**



EC443 EM Transmitting Media

**Instructor: Prof. Esmat Abel Fattah
Tutorial : Eng. Abdel Elah Maged**

Problems Set #7

P1.1 A TE₁₁ mode is propagating through a circular wave guide . the radius of the guide is 5 cm and the guide contains air

- a- determine the cutoff frequency
- b- Determine the wave length in the guide for operating frequency 3 Ghz
- c- determine the wave impedance Z_g in the wave guide.

P1.2 - an air-filled circular wave guide has a radius of 2 cm and is to carry energy at frequency of 10 Ghz. Find all the TE and TM modes for which energy transmission is possible.

P1.3 a circular wave guide has a cutoff frequency of 9 GHZ in the dominant mode:

- a- Find the inside diameter of the guide, if it is air filled
- b- determine the inside diameter of the guides if it is filled with dielectric having a dielectric constant equals 4

P1.4 air- filled circular waveguide has a radius of 1.5 cm and is to carry energy at a frequency of 10Ghz. Find all TE and TM modes for which transmission is possible

P1.5 -an air-filled circular wave guide of radius 2 cm

Find the cutoff frequency of this mode. If the guide is to be filled with dielectric with constant= 2.25, to what value must its radius be changed in order to maintain the cut off frequency at its original value.

P1.6 an air-filled circular wave guide is to be operated at a frequency $f=6$ Ghz and is to have dimensions such that $f_c=0.8f$ for the dominant mode. Find the guides diameter , the guided wave length and the velocity v in the guide.

P1.7-find the radius of a circular wave guide designed to operate in the dominant mode with $f_c=3.2$ Ghz. Find the cut off frequency of the following mode. If the guide is filled with lossless dielectric with constant =4 what will be the cutoff frequency in this case

P1.8-find the cut off frequency of the 1st two propagating wave guide with $a=0.5$ cm
And dielectric constant of 2.25.

If the guide is silver plated and the dielectric loss tangent is 0.001, calculate the attenuation in db for a 50 cm length of the guide operating at 13Ghz. The conductivity of the silver is 6.17×10^7 S/m

P1.9- a rectangular wave guide is to be connected to a circular wave guide. If the cutoff frequency of the dominant modes of both guides is the same. Find:

- a- the radius of the circular wave guide if the width of the rectangular wave guide equals 2.286cm. $b=1.016$ cm.
- b- the max. frequency that can be used such that only the dominant mode in both guides can propagate
- c- the wave impedance at a frequency midway between the cutoff frequency and the max. frequency determined in part b

Good Luck☺