



Arab Academy for Science, Technology & Maritime Transport
COLLEGE OF ENGINEERING & TECHNOLOGY

Department : Computer Engineering Department

Course : Computer Organization

Course Code: CC 312

Lecturer : Dr. Ahmed Abou El-Farag, Dr. Marwa El-Shenawy

L.A / G.T.A : Eng. Maan Khedr ,Eng. Mohamed Wasfy, Eng. Mohamed Tamer

Sheet #4

1) Consider the following mathematical expressions:

a) $A = [(C + D) \times (E - F)] / B$

b) $Z = (W \times V)^2$

Write a program to evaluate these expressions using:

- 3 address instructions
- 2 address instructions
- 1 address instructions
- Zero address instructions

2) Get the content of AC in each of the following addressing modes after executing:

a) LOAD 201.

b) ADD 500

- Direct
- Indirect
- Immediate
- Indexed

$XR = 100$

Address	Memory
200	
201	500
202	
399	450
400	700
500	800
600	900
702	325
800	300